

FLX Date Codes

- + Date code formula:
 - 1 letter (for the year) / 3 digit number (day of year) / 1 letter (for the mfg plant) / 2 digits (for the tank they were charged in)

- + Legend for year
 - **S** = 2010
 - **T** = 2011
 - **U** = 2012

- + For example - T232W22 = Aug 20, 2011
 - **T** = 2011
 - **232** = day of year for August 20
 - **W** = Waynesboro, GA
 - **22** = Charging tank 22

FLX Date Code



FIAMM FLX Installation Tips

- + Torque Spec – 88-106 in lbs (1/4” x 20 hardware on all FLX batteries)
- + Float Voltage – **2.27 v/cell at 77° F**
- + Boost / Equalize / Initial / Freshening charge – If necessary 2.35 to 2.40 v/cell for 48 hours (current limited)
 - Batteries shipped by FIAMM are typically 10-14 days “old” and an initial charge is not required
 - Provide a boost charge prior to performing capacity or acceptance testing